


Last information update: March 2025

**Product configuration: 176B.01**

176B: Ø59 Tech - Pendant system for 48V track - BLE Casambi - Flood Beam

**Product code**

176B: Ø59 Tech - Pendant system for 48V track - BLE Casambi - Flood Beam

**Technical description**

Ø59 mm technical cylindrical pendant system including an adapter for installation on 48V low voltage track ideal for zenithal accent lighting. The adapter made of a thermoplastic material includes the DC/DC driver circuit and Bluetooth protocol. Integrated «Bluetooth Casambi» technology allows each light module inserted on the track to be adjusted independently. Bluetooth Low Energy (Casambi) technology. Frequency 2.4 GHz BLE. The luminaire can be controlled with the Casambi App that enables on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via Smart Light Control (iBeacon) that enables functions including push notification and indoor navigation-wayfinding. Fixed optic lighting system with a high definition reflector made of metallised thermoplastic. The LEDs are set back to minimize glare and guarantee a high level of visual comfort. Structural cylinder made of painted extruded aluminium with an inner ring made of thermoplastic available in different painted or metallised finishes. Glass cover PVC power/pendant cable that can be cut to the required length, in the same colour as the external finish. Tool-free electrical and mechanical adapter connection to the track with a tear-proof safety device.

**Installation**

An adapter is used to fix the device mechanically and tool-free to the 48V track. Max luminaire-luminaire distance (\*): 8 m; max smartphone-luminaire distance (\*): 20 m.

**Colour**

White (01)

**Weight (Kg)**

0.45

**Mounting**

lv track pendant

**Wiring**

Direct connection on 48V track. Track power supply unit to be ordered separately. Luminaire that can be controlled with Bluetooth technology (Casambi).

**Notes**

(\*) The maximum distance for Bluetooth installations is affected by physical obstacles, like walls, metal panels and the layout of the system. We suggest that a test is conducted at the installation site. Technical and anti-glare accessories available; with option of the combined installation of two internal accessories.

A wide range of decorative accessories and diffusers is available.

Complies with EN60598-1 and pertinent regulations

**Technical data**

Im system:	1031.8	MacAdam Step:	2
W system:	13.9	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25C)
Im source:	1340	Voltage [Vin]:	48
W source:	13	Lamp code:	LED
Luminous efficiency (Im/W, real value):	74.23	Number of lamps for optical assembly:	1
Im in emergency mode:	-	ZVEI Code:	LED
Total light flux at or above an angle of 90° [Lm]:	0.0	Number of optical assemblies:	1
Light Output Ratio (L.O.R.) [%]:	77	Power factor:	See installation instructions
Beam angle [°]:	42°	Minimum dimming %:	1
CRI:	90	Overvoltage protection:	0kV Common mode & 0kV Differential mode
Colour temperature [K]:	3000	Control:	Casambi