

## Palco Low Voltage


Design Artec  
Studio

iGuzzini

Last information update: June 2025

### Product configuration: 990A.01

990A.01: Palco LV spotlight Ø 62 - Flood beam - BLE Casambi - 19.7W 1833lm - 4000K - CRI 90 - White



### Product code

990A.01: Palco LV spotlight Ø 62 - Flood beam - BLE Casambi - 19.7W 1833lm - 4000K - CRI 90 - White

### Technical description

Adjustable spotlight with adapter for installation on 48V low voltage track. Made of die-cast aluminium with passive dissipation system. The adapter made of a thermoplastic material includes the DC/DC driver circuit and Bluetooth protocol. Integrated «Bluetooth Casambi» technology allows each light module on the track to be adjusted separately. The swivel joints allow the spotlight to be rotated by 360° and tilted by 90°. The set back position of the optic unit guarantees a high level of visual comfort. Superpure aluminium reflector with high definition OPTI BEAM technology. A rapid tool-free system for connecting the adapter electrically and mechanically to the track. The 48V track coupling device is fitted with a mechanical anti-fall safety double block. Luminaire with Bluetooth Low Energy technology (Casambi). Frequency 2.4 GHz BLE. The luminaire can be controlled with the Casambi App that enables on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via Smart Light Control (iBeacon) that enables functions including push notification and indoor navigation-wayfinding.

### Installation

An adapter is used to fix the device mechanically and tool-free to the 48V track. Max luminaire-luminaire distance (\*): 8 m; max smartphone-luminaire distance (\*): 20 m.

### Colour

White (01)

### Weight (Kg)

0.41

### Mounting

Low voltage track

### Wiring

Direct connection on 48V track. Track power supply unit to be ordered separately. Luminaire can be controlled with Bluetooth technology (Casambi)

### Notes

(\*) The maximum distance for Bluetooth installations is affected by physical obstacles, like walls, metal panels and the layout of the system. We suggest that a test is conducted at the installation site. Technical and anti-glare accessories available; with option of the combined installation of two internal accessories.


Complies with EN60598-1 and pertinent regulations



### Technical data

Im system:	1833	Colour temperature [K]:	4000
W system:	19.7	MacAdam Step:	2
Im source:	2350	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25°C)
W source:	18	Voltage [Vin]:	48
Luminous efficiency (Im/W, real value):	93	Lamp code:	LED
Im in emergency mode:	-	Number of lamps for optical assembly:	1
Total light flux at or above an angle of 90° [Lm]:	0	ZVEI Code:	LED
Light Output Ratio (L.O.R.) [%]:	78	Number of optical assemblies:	1
Beam angle [°]:	26°	LED current [mA]:	520
CRI (minimum):	90	Power factor:	See installation instructions
Rf (Colour Fidelity Index):	90	Minimum dimming %:	1
Rg (Gamut Index):	98	Control:	Casambi

### Polar

Imax=8259 cd		Lux			
		h	d	Em	Emax
		8	3.6	104	129
		16	7.3	26	32
		24	10.9	12	14
		32	14.6	6	8
α = 26°					

# Isolux

