

Last information update: March 2025

**Product configuration: S085**

S085: Spotlight with bracket - Neutral White LED - CRI 80 - Integrated power supply - STWt1.5 optic - Ta 40°

**Product code**

S085: Spotlight with bracket - Neutral White LED - CRI 80 - Integrated power supply - STWt1.5 optic - Ta 40°

**Technical description**

Spotlight designed to use LED lamps and an STWt1.5 optic. Consists of a die-cast aluminium optical assembly and box for the power supply, a steel bracket and a clear, tempered sodium-calcium safety glass cover. The luminaire is fitted with a double cable gland for pass-through wiring. The optical assembly can be adjusted on a horizontal plane at an angle between -50° / +90°. Agorà is fitted with a graduated scale and mechanical locking device for positioning. The street optics system comes complete with a Neutral White monochrome LED circuit. The electronic DALI power supply is integrated in the product and compatible with remote management systems. Compatible with programming systems via DALI terminals or an NFC system. Both indoor (diffuser glass covers, lamellar louvers and refractors for elliptical light) and outdoor accessories (cylindrical screens, visors and protective grilles) can be used. All external screws used are made of A2 stainless steel.

**Installation**

Floor, ceiling, wall or pole-mounted installation.

**Colour**

White (01) | Black (04) | Grey (15) | Rust Brown (F5)

**Weight (Kg)**

7

**Mounting**

wall surface|ceiling surface|free standing

**Wiring**


Double PG.

Complies with EN60598-1 and pertinent regulations



IK08

IP66

**Technical data**

Im system:	3350.0	Life Time LED 1:	100,000h - L90 - B10 (Ta 25C)
W system:	26.2	Life Time LED 2:	100,000h - L90 - B10 (Ta 40C)
Im source:	3350	Lamp code:	LED
W source:	23	Number of lamps for optical assembly:	1
Luminous efficiency (lm/W, real value):	127.86	ZVEI Code:	LED
Im in emergency mode:	-	Number of optical assemblies:	1
Total light flux at or above an angle of 90° [Lm]:	0.0	Intervallo temperatura ambiente:	from -30°C to 50°C.
Light Output Ratio (L.O.R.) [%]:	100	Power factor:	See installation instructions
Beam angle [°]:	138° / 66°	Inrush current:	21 A / 300 µs
CRI:	80	Maximum number of luminaires of this type per miniature circuit breaker:	B10A: 13 luminaires B16A: 21 luminaires C10A: 21 luminaires C16A: 35 luminaires
Colour temperature [K]:	4000	Overvoltage protection:	0kV Common mode & 0kV Differential mode
MacAdam Step:	3	Control:	DALI-2