iGuzzini

Last information update: May 2025

Product configuration: 120C

120C: LV Ø80 pendant projector for Filorail - Optibeam Reflector - DALI Powerline

Product code

120C: LV Ø80 pendant projector for Filorail - Optibeam Reflector - DALI Powerline

Technical description

Miniaturised adjustable pendant luminaire with adapter for installation on a 48V Filorail low voltage track. High yield LED lamp with high color rendering index. Adjustable pendant spotlight made of die-cast aluminium and thermoplastic material. Balanced pendant system with double steel cable - L max 2000 mm - and adjustment system. DC/DC driver circuit with dimmable DALI function integrated in the body. The Dali «power line» technology allows each spotlight on the track to be adjusted separately. Luminaire body made of die-cast aluminium and thermoplastic material. Swivel joints allow the spotlight to be rotated by 360° about the vertical axis and tilted by 90° tilting relative to the horizontal plane. The set back position of the optic unit guarantees a high level of visual comfort. Optibeam Reflector in high-efficiency, metallized plastic. Mechanical aiming locks fitted on both the spotlight and adapter allow rotation and tilting movements to be locked in position to ensure efficient light aiming even after the original installation or during maintenance. The optical assembly is equipped with an accessory holding ring designed to contain a flat accessory. Another external component that rotates freely around the spotlight's longitudinal axis can also be applied.

Installation

Installation on a Filorail track.

Colour

White (01) | Orange (02) | Black (04) | Red (05) | Yellow (06) | Sky blue (09)

Mounting

Low voltage track

Wiring

LED driver integrated in product body - direct connection on 48V track. Track power supply unit to be ordered separately.

Complies with EN60598-1 and pertinent regulations



Im system:1383.2Colour temperature [K]:3500W system:14.8MacAdam Step:2Im source:1820Life Time LED 1:> 50,000h - L90 - B10 (Ta 25C)W source:14Voltage [Vin]:48Luminous efficiency (Im/W, real value):93.46Lamp code:LEDIm in emergency mode:-assembly:Total light flux at or above an angle of 90° [Lm]:0.0ZVEI Code:LEDLight Output Ratio (L.O.R.)76Semblies: Control:Control:DALI	Technical data			
Im source: 1820 Life Time LED 1: > 50,000h - L90 - B10 (Ta 25C) W source: 14 Voltage [Vin]: 48 Luminous efficiency (Im/W, 93.46 Lamp code: LED real value): Number of lamps for optical 1 1 Im in emergency mode: - assembly: 2VEI Code: LED Total light flux at or above an angle of 90° [Lm]: 0.0 ZVEI Code: LED Light Output Ratio (L.O.R.) 76 assemblies: Control: DALI Beam angle [°]: 28° 28° 28° 28°	Im system:	1383.2	Colour temperature [K]:	3500
W source: 14 Voltage [Vin]: 48 Luminous efficiency (Im/W, 93.46 Lamp code: LED real value): Number of lamps for optical 1 1 Im in emergency mode: - assembly: Total light flux at or above an angle of 90° [Lm]: 0.0 ZVEI Code: LED Light Output Ratio (L.O.R.) 76 assemblies: Control: DALI Beam angle [°]: 28° 28° DALI	W system:	14.8	MacAdam Step:	2
Luminous efficiency (Im/W, 93.46 Lamp code: LED real value): Number of lamps for optical 1 Im in emergency mode: - Total light flux at or above an angle of 90° [Lm]: 0.0 Light Output Ratio (L.O.R.) 76 [%]: 28°	Im source:	1820	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25C)
real value): Number of lamps for optical 1 Im in emergency mode: Total light flux at or above 0.0 an angle of 90° [Lm]: Light Output Ratio (L.O.R.) 76 [%]: Beam angle [°]: 28° Number of optical 1 Important Structure	W source:	14	Voltage [Vin]:	48
Im in emergency mode: - assembly: Total light flux at or above 0.0 ZVEI Code: LED an angle of 90° [Lm]: Number of optical 1 Light Output Ratio (L.O.R.) 76 assemblies: [%]: Control: DALI	Luminous efficiency (Im/W,	93.46	Lamp code:	LED
Total light flux at or above 0.0 ZVEI Code: LED an angle of 90° [Lm]: Number of optical 1 Light Output Ratio (L.O.R.) 76 assemblies: [%]: Control: DALI	real value):		Number of lamps for optical	1
an angle of 90° [Lm]: Number of optical 1 Light Output Ratio (L.O.R.) 76 assemblies: [%]: Control: DALI Beam angle [°]: 28°	Im in emergency mode:	-	assembly:	
Light Output Ratio (L.O.R.) 76 assemblies: [%]: Control: DALI Beam angle [°]: 28°	0	0.0	ZVEI Code:	LED
[%]: Control: DALI Beam angle [°]: 28° DALI			Number of optical	1
Beam angle [°]: 28°	• • • • •	76	assemblies:	
			Control:	DALI
	Beam angle [°]:	28°		
CRI: 90	CRI:	90		