

DALI IP20 10/17W constant current power supply - for 2 Crystal recessed luminaires

Last information update: January 2025



Accessory code

PD56: DALI IP20 10/17W constant current power supply - for 2 Crystal recessed luminaires

Technical description

DALI 10/17W dimmable constant current electronic power supply.
 Input Vin=220÷240 Vac 50÷60Hz.
 SELV output.
 The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

Installation

Compatible with opening for Crystal recessed fitting assembly.

Colour	Weight (Kg)	Dimension (mm) (*)
Indeterminate (00)	0.16	166x51x29.2
* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.		

Wiring

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.
 Cable clamp on primary and secondary.

Notes

SELV

Complies with EN60598-1 and pertinent regulations



Technical data

Current out [mA]:	280	Control:	DALI-2
-------------------	-----	----------	--------