

DALI IP20 35W constant current power supply - for 3 Crystal recessed luminaires

Design iGuzzini

iGuzzini

Last information update: January 2025



Accessory code

PD63: DALI IP20 35W constant current power supply - for 3 Crystal recessed luminaires

Technical description

DALI 35 W dimmable constant current electronic power supply.

Input Vin=220÷240 Vac 50÷60Hz.

SELV output.

The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

Installation

Compatible with opening for Crystal recessed fitting assembly.

Colour

Indeterminate (00)

Weight (Kg)

0.15

Dimension (mm) (*)

169x67x30

* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

Wiring

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.

Cable clamp on primary and secondary.

Notes

SELV

Complies with EN60598-1 and pertinent regulations



IP20



Technical data

Current out [mA]:

820

Control:

DALI-2