

**DALI IP20 25/36W constant current power supply - for 2 Crystal recessed luminaires**

Last information update: January 2025



**Accessory code**

PD65: DALI IP20 25/36W constant current power supply - for 2 Crystal recessed luminaires

**Technical description**

DALI 25/36 W dimmable constant current electronic power supply.  
 Input Vin=220÷240 Vac 50÷60Hz.  
 SELV output.  
 The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

**Installation**

Compatible with opening for Crystal recessed fitting assembly.

Colour	Weight (Kg)	Dimension (mm) (*)
Indeterminate (00)	0.15	169x67x30
* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.		

**Wiring**

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.  
 Cable clamp on primary and secondary.

**Notes**

SELV

Complies with EN60598-1 and pertinent regulations



**Technical data**

Current out [mA]:	665	Control:	DALI-2
-------------------	-----	----------	--------