

## DALI IP20 10/17W constant current power supply - for 3 Crystal HO Tunable White recessed luminaires

Design iGuzzini

iGuzzini

Last information update: January 2025



### Accessory code

PD85: DALI IP20 10/17W constant current power supply - for 3 Crystal HO Tunable White recessed luminaires

### Technical description

DALI 10/17 W dimmable constant current electronic power supply.

Can be used for HO Tunable White models.

Input Vin=220÷240 Vac 50÷60Hz.

SELV output.

The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

### Installation

Compatible with opening for Crystal recessed fitting assembly.

### Colour

Indeterminate (00)

### Weight (Kg)

0.23

### Dimension (mm) (\*)

166x51x29.2

\* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

### Wiring

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.

Cable clamp on primary and secondary.

### Notes

DT8 type DALI check. 1 address, 1 DALI load (2 mA).

Complies with EN60598-1 and pertinent regulations



IP20



### Technical data

Frequency [Hz]: 0/50/60

Current out [mA]: 900

Inrush current: 29 A / 153 µs

Maximum number of LED power supply units of this type per miniature circuit breaker:

B10A: 32 power supply units

B16A: 51 power supply units

C10A: 53 power supply units

C16A: 86 power supply units

Minimum dimming %: 1

Overvoltage protection: 2kV Common mode & 1kV Differential mode

Control: DALI-2