

## DALI IP20 15/36W constant current power supply - for 2 Crystal recessed luminaires

Design iGuzzini

iGuzzini

Last information update: January 2025



### Accessory code

PD74: DALI IP20 15/36W constant current power supply - for 2 Crystal recessed luminaires

### Technical description

DALI 15/36 W dimmable constant current electronic power supply.

Input Vin=220÷240 Vac 50÷60Hz.

SELV output.

The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

### Installation

Compatible with opening for Crystal recessed fitting assembly.

### Colour

Indeterminate (00)

### Weight (Kg)

0.15

### Dimension (mm) (\*)

169x67x31

\* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

### Wiring

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.

Cable clamp on primary and secondary.

### Notes

SELV

Complies with EN60598-1 and pertinent regulations



IP20



### Technical data

Current out [mA]:

515

Control:

DALI-2