

## Constant current power supply unit DALI IP20 10W - Vin = 220 ÷ 240Vac 50 / 60Hz Iout = 200mA

Design iGuzzini

iGuzzini

Last information update: January 2024



### Accessory code

PG40: Constant current power supply unit DALI IP20 10W - Vin = 220 ÷ 240Vac 50 / 60Hz Iout = 200mA

### Technical description

DALI constant current dimmable power supply I=200 mA 10 W. Input Vin=220÷240 Vac 50÷60 Hz. SELV output. Product features include short circuit protection, overcurrent and overtemperature protection.

### Installation

Check the height required for the assembly (see the luminaire instructions sheet). Fitted with slots for fastening with screws, if required.

Colour	Weight (Kg)	Dimension (mm) (*)
Indeterminate (00)	0.12	166x30x22

\* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

### Wiring

Input and output terminals on opposite sides (cable cross-section up to 1.5 mm<sup>2</sup>).

Cable clamp on primary+DALI and secondary. The power supply is fitted with a cable and fast-connector to make the connection to the luminaire easier.

### Notes

SELV, EL

Complies with EN60598-1 and pertinent regulations



### Technical data

Frequency [Hz]:	0/50/60	Minimum dimming %:	1
Current out [mA]:	200	Overvoltage protection:	2kV Common mode & 1kV Differential mode
Inrush current:	5 A / - μs	Control:	DALI-2
Maximum number of LED power supply units of this type per miniature circuit breaker:	B10A: 81 power supply units B16A: 130 power supply units C10A: 135 power supply units C16A: 221 power supply units		