

Electronic power supply for Trick RGB

Last information update: July 2024



Accessory code
MZ74: Electronic power supply for Trick RGB

Technical description
Independent IP20 Maxi Jolly ballast, for internal use. Electronic ballast 50W@48V (1050mA max). Includes thermal and short circuit protections and against mains overvoltages and overloads.

Colour	Weight (Kg)	Dimension (mm) (*)
Indeterminate (00)	0.15	125x80x22
* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.		
Complies with EN60598-1 and pertinent regulations		



Technical data			
Frequency [Hz]:	50/60	Maximum number of LED power supply units of this type per miniature circuit breaker:	B10A: 18 power supply units B16A: 30 power supply units C10A: 31 power supply units C16A: 51 power supply units
Current out [mA]:	48		
Inrush current:	10 A / 200 μs		
		Overvoltage protection:	