

Electronic power supply for Trick RGB

Design iGuzzini

iGuzzini

Last information update: February 2023



Accessory code

MZ74: Electronic power supply for Trick RGB

Technical description

Independent IP20 Maxi Jolly ballast, for internal use. Electronic ballast 50W@48V (1050mA max). Includes thermal and short circuit protections and against mains overvoltages and overloads.

Colour	Weight (Kg)	Dimension (mm) (*)
Indeterminate (00)	0.15	125x80x22
* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.		
Complies with EN60598-1 and pertinent regulations		



Technical data

Frequency [Hz]:	50/60	Maximum number of LED power supply units of this type per miniature circuit breaker:	B10A: 18 power supply units
Current out [mA]:	48		B16A: 30 power supply units
Inrush current:	10 A / 200 µs		C10A: 31 power supply units
		Overvoltage protection:	C16A: 51 power supply units
			5kV Common mode & 4kV Differential mode